

BiPAC 7300 Series Firmware Emergency Upgrade

Index

Step1 : Set Fixed IP	2
Step2 : Set Device	7
Step3 : Upgrade firmware	8

Step1 : Set Fixed IP

1.Press Start->Setting->Control Panel

🄗 My Docume		P aint				
My Comput	er v307(20071	reget.bat				
- S		<u>è</u>				
My Netwo Places	rk BitComet	Shortcut to sw_fw on 1				
1	300	<u> </u>				
Recycle Bi	n Chariot Console	Smart VPN Client				
	_					
	Windows Catalog	JeYP.				
-	Windows Update	120F-111				
8	新增 Office 文件					
2	開啓 Office 文件	*_Ser				
a	Programs	•				
Ì	Documents	•				
al 🛐	Settings	Control Panel				
	Search	Network Connections Printers and Faxes	; •			
Prof	Help and Support	Taskbar and Start Mer	enu			
×	Run					
	Log Off user					
	Turn Off Computer					
🏄 sta	rt 🛛 📀	Ø Ø				EN

2.Click "Network Connections" icon



3. Click network adapter icon which connected 7300 device



4.Click 「Properties」 button

📥 Local Area Con	nection Status	? 🗙
General Support		
Connection		
Status:		Connected
Duration:		00:26:55
Speed:		100.0 Mbps
Signal Strength:		
Activity	Sent — ᇌ —	Received
Packets:	290	163
	<u>D</u> isable	

5.Click [Internet Protocol(TCP/IP)] and then click [Properties] button



6.Set fixed IP like below image

nternet Protocol (TCP/IP) Properties 🛛 🔹 💽 🔀					
General					
You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.					
O Use the following IP address:					
<u>I</u> P address:	192.168.1.11				
S <u>u</u> bnet mask:	255 . 255 . 255 . 0				
Default gateway:	· · ·				
Obtain DNS server address automatically O Use the following DNS server addresses:					
Alternate DNS server:					
Ad <u>v</u> anced					
OK Cancel					

Step2 : Set Device

1.Press device $\[\] RESET \]$ button and don't set free

2.Press 「Power switch」 button to power off and power on the device

3.Set free with $\lceil RESET \rfloor$ button till indicate $\lceil SYS \rfloor$ LED light stationary





Step3 : Upgrade firmware

1.Click Windows 「start」 -> 「Programs」 -> 「Internet Explorer」

My Docume	ents TheGreenBow VPN	W Paint		
My Compu	ت الter v307(20071	reget.bat		
My Netwo Places	prk BitComet	Shortcut to sw_fw on 1		
🥫 Recycle E	Sin Chariot Console	Smart VPN Client		
	Windows Catalog Windows Update 新增 Office 文件 開啓 Office 文件	/sxP		
	Programs Documents			
Professiona	Settings Search Help and Support	MSN Explorer Finds and displays information and Web sites on the Internet. Control Assistance Windows Media Player		
dows XP	Run	Will dows Media Player [™] Mindows Messenger [™] DrayTek Smart VPN Client [™] NetMeter		
ž 👩	Turn Off Computer.	Image: Signature Image: Signature <tr< td=""><td>EN</td><td>📸 🛒 🙀 🛄 10:19 AM</td></tr<>	EN	📸 🛒 🙀 🛄 10:19 AM

2.Type \lceil <u>http://192.168.1.254</u> \rfloor and press \lceil Browse \rfloor button



3.Choose the firmware and press $\ ^{\lceil} \mbox{Open} \ _{\ }$ button

Choose file		? 🛛
Look <u>i</u> n:	🖙 Local Disk (C:) 💽 💽 📴	
My Recent Documents Desktop My Documents My Computer	 Documents and Settings Intel 802.11g WLAN Downloads Program Files WINDOWS BG30.107 PCRange-7300A-V1.35-RC44-699_sso_billion.afw PCRange-7300A-V1.35-RC44-699_sso_billion.sfw adsldiag 1 3 2 PCRange-7300GA-V1.35-RC48-682.80.3_sso_billion.afw 	
My Network Places	File name: PCRange-7300GA-V1.35-RC48-682.80.3_sso_I Files of type: All Files (*.*)	<u>D</u> pen Cancel

4.After choose firmware , press START button to upgrade firmware



5.Press $\lceil OK \rfloor$ button in message box



6.Press 「OK」 button in message box again



7. Waiting firmware upgrade process about 3~4 minutes



8.Firmware upgrade complete

🗿 ADSL Firewall Router - Microsoft Internet Explorer					
File Edit View Favorites Tools Help					
🌀 Back 🝷 🐑 💌 🛃 🍏) 🔎 Search 🤺 Favorites 🔇 Med	ia 🚱 🔗 🍓 🔜 🔜 ᡝ 🏭			
Address 🕘 http://192.168.1.254/index.ht	tm			💌 🄁 Go	Links »
BILLION	ADSL Firewall Router			Powering contr with Sec	urictions Urity
Status	Status				
Quick Start	Device Information				
Configuration	Model Name	BIPAC 7300GA			
Save Config to FLASH	Host Name 💽	home.gateway			
	System Up-Time	0 min(s)			
	Current Time 💽	Sat Jan 1 00:00:43 2000			
	Hardware Version	TRENDCHIP TC3162			
	Software Version	1.35-RC48-682.80.3_sso_billion			
	Bootrom Version	1.06			
	MAC Address	00:04:ed:0a:26:35			
	Home URL	Billion Electric Co, PC Range Pty Ltd.			
	LAN				
	IP Address 💽	192.168.1.254			
	SubNetmask	255.255.255.0			
	DHCP Server 💽	DHCP Server Running			
	WAN				
	ipwan 💽	PPPoE LLC			
	VPL/ VCI	8 / 35			
	Connection	Disconnected Connect			~
			SAVE CONFIG	RESTART	
🙆 Done				🥑 Internet	

9.Chnage network adapter's setting to \ulcorner Obtain an IP address automatically \lrcorner

and $\ ^{\lceil}$ Obtain DNS server address automatically $_{\bot}$ option.

Internet Protocol (TCP/IP) Prope	rties 🛛 🛛 🛛 🔀			
General Alternate Configuration				
You can get IP settings assigned automatically if your network supports this capability. Otherwise, you need to ask your network administrator for the appropriate IP settings.				
Obtain an IP address automatical	y			
Use the following IP address: —				
IP address:				
Sybnet mask:				
<u>D</u> efault gateway:				
⊙ (0 <u>b</u> tain DNS server address autor	natically			
OUse the following DNS server add	dresses:			
Preferred DNS server:	· · · · · ·			
<u>A</u> lternate DNS server:				
	Ad <u>v</u> anced			
	OK Cancel			