



How to set port forwarding rules with a Bipac 7800N

Please login to the router configuration page by opening Internet Explorer and typing in the address bar <http://192.168.1.254>, as shown below.



You will be prompted with a Login page as shown below, please use the username 'admin' and the password 'admin' (case sensitive)



Now click on 'Advanced' on the left hand column, followed by 'Configuration' >> 'Virtual Server' >> 'Port Mapping'.

Now enter a application name, for this example we used 'Apple_TV' now enter the protocol you wish to use, we used 'TCP' and then enter the ports you wish to open, followed by the IP address of the device you wish to open the ports too. Finally click on 'Add' to add the rule.

This is shown in the screen shot below.

BILLION Dual WAN ADSL2+ Firewall Router

Powering communications with Security

Advanced

- Advanced
- Status
- Quick Start
- Configuration
- LAN
- WAN
- System
- Firewall
- QoS
- Virtual Server
- Port Mapping
- DMZ
- ALG
- Wake on LAN
- Certificate
- Time Schedule
- Advanced

Configuration

Enter a application name for this example we used Apple_TV

Port Mapping

Parameters

Application: Apple_TV

Protocol: TCP

External Port: 3689 ~ 3689

Internal IP Address: 192.168.1.100

Internal Port: 3689

Time Schedule: Always On

Port ranges forwarded internally will be the same as Externally.

Buttons: Add, Edit / Delete

Enter the ports you wish to forward

Enter the IP address you wish to forward too

Select the Protocol, eg TCP,UDP

Click on 'Add' to add the rule.

Save Config Restart Logout

Copyright @ Billion Electric Co., Ltd. All rights reserved.

You should now see your added rule, as shown below.

Configuration

Port Mapping

Parameters

Application: --select--

Protocol: TCP

External Port: ~

Internal IP Address: --select--

Internal Port: ~

Time Schedule: Always On

Port ranges forwarded internally will be the same as Externally.

Buttons: Add, Edit / Delete

Edit	Application	Protocol	External Port	Internal IP Address	Internal Port	Time Schedule	Delete
<input type="radio"/>	Apple_TV	TCP	3689	192.168.1.100	3689	Always On	<input type="checkbox"/>

You should see you added rule here

Now follow the steps again if you wish to open more ports.